

INSTRUCTIONS FOR HERESY H-700

DESCRIPTION

The HERESY is a 3-way, 8 ohm loudspeaker system. The bass is a 12" woofer in a total enclosure, the squawker and tweeter are horn loaded for maximum performance and minimum distortion. Crossover frequencies are 700 Hz and 6000 Hz.

PLACEMENT

The HERESY should be used upright but may be used on its side with a slight loss in high frequency performance. The HERESY, like **ALL** other speakers, sounds better in a corner. Don't take our word for it, try it yourself.

HOOK UP

We do not recommend amplifiers in excess of 105 watts per channel.

Use rubber or plastic coated lamp cord of no smaller than 18 A. W. G. Connect to terminal strip on rear of speaker system. The red painted terminal is positive. We suggest placing a 1 ampere (2 ampere maximum) fast blow fuse in the speaker line for added protection in case of amplifier failure or misuse.